



PKN Controls Digital Amplifier - základní údaje

Digital Amplifier type	XD-2500	XD-4000	XD-6000	XE-2500	XE-4000	XE-6000	LC-2002	LC-4004
POWER @ 16 Ohms	2x 320W	2x 680W	2x 1000W	2x 320W	2x 680W	2x 1000W	2x 300W	4x 300W
POWER @ 8 Ohms	2x 650W	2x 1400W	2x 1900W	2x 650W	2x 1400W	2x 1900W	2x 500W	4x 500W
POWER @ 4 Ohms	2x 1250W	2x 2100W	2x 3650W	2x 1250W	2x 2100W	2x 3650W	2x 1000W	4x 1000W
POWER @ 2.6 Ohms	2x 1900W	2x 2000W	2x 3000W	2x 1900W	2x 2000W	2x 3000W	2x 1800W	4x 1800W
POWER @ 2 Ohms	2x 1500W	2x 1800W*	2x 2200W*	2x 1500W	2x 1800W*	2x 2200W*	2x 1600W	4x 1600W
Out Peak Voltage	105V	160V	185V	105V	160V	185V	100V	100V
Out Peak Current	41A	43A	50A	41A	43A	50A	40A	40A
Max. Main Power (AC 230V)	3800W	4200W	7300W	3800W	4200W	7300W	3600W	7200W
Bridge @ 16 Ohm	No Bridge						1x 1300W	2x 1300W
Bridge @ 8 Ohm		No Bridge	No Bridge	No Bridge	No Bridge	No Bridge	1x 2000W	2x 2000W
Bridge @ 4 Ohm							1x 1800W	2x 1800W
Average Current Draw (Normal Music, 0 Db)	5A	10A	15A	5A	10A	15A	4A	8A
Max. Current Draw (AC 230V)	16A	25A	36A	16A	25A	36A	9A	18A

(*) Nedoporučované zapojení